

LED Goldstar FMM Non-Maintained Emergency



Catalogue No:
FMM9992/3/6/FP

Description:
Self Contained Non-Maintained LED
Emergency Luminaire.

Famco MasterMinder Computer
Monitoring and Control System

Complete with Flex & Plug.

Designed for Either Accessible or
Inaccessible Ceilings with Concealed
Mounting Clip Fixing.

LED Goldstar Kit includes Three
Different Size Trims for Multiple Cutout
Options.

Additional Options:

- Clear Dome Cover - Add /CC to Product Code when Ordering
- Black Version - Add /BL to Product Code when Ordering.

Australian conceived,
designed & manufactured.

www.famco.com.au



MAXIMUM PERMISSIBLE SPACING FOR EMERGENCY LUMINAIRES

PHOTOMETRIC CLASSIFICATION	MOUNTING HEIGHT - M															
	2.1	2.4	2.7	3.0	3.3	3.6	4.0	4.5	5	6	7	8	9	10	15	20
F9992/F9993 C0 D40	16.7	17.4	18.0	18.6	19.1	19.6	20.1	20.8	21.3	22.1	22.7	23.0	23.1	23.1	19.4	
/F9996 D40	16.7	17.4	18.0	18.6	19.1	19.6	20.1	20.8	21.3	22.1	22.7	23.0	23.1	23.1	19.4	

FAMCO LIGHTING PTY LTD
ACN 091 160 440 ABN 22 091 160 440
100 Rupert St, Collingwood 3066
(Melbourne), Victoria, Australia

T: (03) 9935 7300
F: (03) 9935 7301
E: info@famco.com.au

Correspondence:
P.O. Box 108,
Abbotsford VIC 3067

© 2011 Famco Lighting Pty Ltd All rights reserved.
E&OE. Subject to change without notice. To allow progress
in design. This document and the information it contains is
the property and copyright of Famco Lighting Pty Ltd and
must not be used, copied, transmitted or reproduced
without our written permission.